
Table of Meta Events

Special Faders

- 46** Assign Alias.
- 47** Send MIDI byte (0-255).
- 48** Cable Switcher.
- 100** Set Logic's tempo temporarily while transport is running. The tempo is 50 plus the meta-event value (range 50-177).

Logic Internal

- 49** Go to screenset (1-99).
- 50** Go to song (0-127). Sends "Song Select" to other MIDI devices.
- 51** Go to marker (0-127).
- 52** Stop playback.

Fader Actions

- 96** Set range minimum.
- 97** Set range maximum.
- 98** Silent Fader (set without sending).
- 99** Bang Fader (causes Fader to send its value). Different bang event values cause different actions:
 - 1 Send current value.
 - 121 Decrement with roll-under then send.
 - 123 Increment with roll-over then send.
 - 125 Decrement without roll-under then send.
 - 127 Increment without roll-over then send.

Even values, one less than shown cause the bang to pass through to all connected Faders.

Transformer Actions

- 122** Set map value for current map position (see #123).
- 123** Set current map position (to receive value - see #122).
- 124** Set max (bottom) parameter for all active, numerical Transformer conditions with two parameters.
- 125** Set min (top) parameter for all active, numerical Transformer conditions.
- 126** Set max (bottom) parameter for all active, numerical Transformer operations with two parameters.
- 127** Set min (top) parameter for all active, numerical Transformer operations